

# 1.0mmW-1.0mmW ADAPTERS **NEW**







## ► Overview

Adapter for 1.00mmW connector and 1.00mmW connector. As a new product, we have developed this adapter with our knowledge and experience of millimeter wave. The product has excellent V.S.W.R. and insertion loss. Electrical length for this series is standardized.

## ► Applications

High frequency measurement, Connections of high speed data-communication devices, optical component, millimeter wave device and modules.

## ► Product

Product : 02R0266-00		ADP 1.0mmW/P – 1.0mmW/P													
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 60GHz <math>\leq 1.3</math> 60 ~ 110GHz <math>\leq 1.4</math></td> </tr> <tr> <td>Insertion loss</td> <td>DC ~ 110GHz 0.6dB 以下</td> </tr> <tr> <td>Connector</td> <td>Material</td> <td>Finish</td> </tr> <tr> <td>1.0mmW/P</td> <td>SUS</td> <td>Pv</td> </tr> <tr> <td>1.0mmW/P</td> <td>SUS</td> <td>Pv</td> </tr> </table>	V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$	Insertion loss	DC ~ 110GHz 0.6dB 以下	Connector	Material	Finish	1.0mmW/P	SUS	Pv	1.0mmW/P	SUS	Pv
V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$														
Insertion loss	DC ~ 110GHz 0.6dB 以下														
Connector	Material	Finish													
1.0mmW/P	SUS	Pv													
1.0mmW/P	SUS	Pv													
		(RoHS)													
Product : 02R0267-00		ADP 1.0mmW/P – 1.0mmW/J													
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 60GHz <math>\leq 1.3</math> 60 ~ 110GHz <math>\leq 1.4</math></td> </tr> <tr> <td>Insertion loss</td> <td>DC ~ 110GHz 0.6dB 以下</td> </tr> <tr> <td>Connector</td> <td>Material</td> <td>Finish</td> </tr> <tr> <td>1.0mmW/P</td> <td>SUS</td> <td>Pv</td> </tr> <tr> <td>1.0mmW/J</td> <td>BeCu</td> <td>Au</td> </tr> </table>	V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$	Insertion loss	DC ~ 110GHz 0.6dB 以下	Connector	Material	Finish	1.0mmW/P	SUS	Pv	1.0mmW/J	BeCu	Au
V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$														
Insertion loss	DC ~ 110GHz 0.6dB 以下														
Connector	Material	Finish													
1.0mmW/P	SUS	Pv													
1.0mmW/J	BeCu	Au													
		(RoHS)													
Product : 02R0268-00		ADP 1.0mmW/J – 1.0mmW/J													
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 60GHz <math>\leq 1.3</math> 60 ~ 110GHz <math>\leq 1.4</math></td> </tr> <tr> <td>Insertion loss</td> <td>DC ~ 110GHz 0.6dB 以下</td> </tr> <tr> <td>Connector</td> <td>Material</td> <td>Finish</td> </tr> <tr> <td>1.0mmW/J</td> <td>BeCu</td> <td>Au</td> </tr> <tr> <td>1.0mmW/J</td> <td>BeCu</td> <td>Au</td> </tr> </table>	V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$	Insertion loss	DC ~ 110GHz 0.6dB 以下	Connector	Material	Finish	1.0mmW/J	BeCu	Au	1.0mmW/J	BeCu	Au
V.S.W.R.	DC ~ 60GHz $\leq 1.3$ 60 ~ 110GHz $\leq 1.4$														
Insertion loss	DC ~ 110GHz 0.6dB 以下														
Connector	Material	Finish													
1.0mmW/J	BeCu	Au													
1.0mmW/J	BeCu	Au													
		(RoHS)													